

Specifications are subject to change without any prior written notice.

*Control of LEDs depends on the Pixel Flip setting.

DMX CHANNEL MODE										VALUE	FUNCTION
1CH:04	2CH:04	6CH	8CH	10CH	12CH	28CH	30CH	32CH	35CH		16 BIT CHANNELS
	1	1	1	1	1						RED LED - All LEDs [1-7]
										0-255	Red (0-Black - 255-100%)
	2	2	2	2	2						GREEN LED - All LEDs [1-7]
										0-255	Green (0-Black - 255-100%)
	3	3	3	3	3						BLUE LED - All LEDs [1-7]
										0-255	Blue (0-Black - 255-100%)
	4	4	4	4	4						WHITE LED - All LEDs [1-7]
										0-255	White (0-Black - 255-100%)
						1	1	1	1		RED LED - LED [1]
										0-255	Red (0-Black - 255-100%)
						2	2	2	2		GREEN LED - LED [1]
										0-255	Green (0-Black - 255-100%)
						3	3	3	3		BLUE LED - LED [1]
										0-255	Blue (0-Black - 255-100%)
						4	4	4	4		WHITE LED - LED [1]
										0-255	White (0-Black - 255-100%)
						5	5	5	5		RED LED - LED [2]
										0-255	Red (0-Black - 255-100%)
						6	6	6	6		GREEN LED - LED [2]
										0-255	Green (0-Black - 255-100%)
						7	7	7	7		BLUE LED - LED [2]
										0-255	Blue (0-Black - 255-100%)
						8	8	8	8		WHITE LED - LED [2]
										0-255	White (0-Black - 255-100%)
						9	9	9	9		RED LED - LED [3]
										0-255	Red (0-Black - 255-100%)
						10	10	10	10		GREEN LED - LED [3]
										0-255	Green (0-Black - 255-100%)
						11	11	11	11		BLUE LED - LED [3]
										0-255	Blue (0-Black - 255-100%)
						12	12	12	12		WHITE LED - LED [3]
										0-255	White (0-Black - 255-100%)
						13	13	13	13		RED LED - LED [4]
										0-255	Red (0-Black - 255-100%)
						14	14	14	14		GREEN LED - LED [4]
										0-255	Green (0-Black - 255-100%)
						15	15	15	15		BLUE LED - LED [4]
										0-255	Blue (0-Black - 255-100%)
						16	16	16	16		WHITE LED - LED [4]
										0-255	White (0-Black - 255-100%)
						17	17	17	17		RED LED - LED [5]
										0-255	Red (0-Black - 255-100%)
						18	18	18	18		GREEN LED - LED [5]
										0-255	Green (0-Black - 255-100%)
						19	19	19	19		BLUE LED - LED [5]
										0-255	Blue (0-Black - 255-100%)
						20	20	20	20		WHITE LED - LED [5]
										0-255	White (0-Black - 255-100%)
						21	21	21	21		RED LED - LED [6]
										0-255	Red (0-Black - 255-100%)
						22	22	22	22		GREEN LED - LED [6]
										0-255	Green (0-Black - 255-100%)
						23	23	23	23		BLUE LED - LED [6]
										0-255	Blue (0-Black - 255-100%)
						24	24	24	24		WHITE LED - LED [6]
										0-255	White (0-Black - 255-100%)

DMX Channel Values / Functions Version 1 (35 DMX Channels)

Specifications are subject to change without any prior written notice.

*Control of LEDs depends on the Pixel Flip setting.

DMX CHANNEL MODE										VALUE	FUNCTION
1CH:04	2CH:04	6CH	8CH	10CH	12CH	28CH	30CH	32CH	35CH		16 BIT CHANNELS
						25	25	25	25	0-255	RED LED - LED [7] Red (0-Black - 255-100%)
						26	26	26	26	0-255	GREEN LED - LED [7] Green (0-Black - 255-100%)
						27	27	27	27	0-255	BLUE LED - LED [7] Blue (0-Black - 255-100%)
						28	28	28	28	0-255	WHITE LED - LED [7] White (0-Black - 255-100%)
1			5		5						COLOR MACROS
										0	NO Function
										1-4	Color Macro 01
										5-8	Color Macro 02
										9-12	Color Macro 03
										13-16	Color Macro 04
										17-20	Color Macro 05
										21-24	Color Macro 06
										25-28	Color Macro 07
										29-32	Color Macro 08
										33-36	Color Macro 09
										37-40	Color Macro 10
										41-44	Color Macro 11
										45-48	Color Macro 12
										49-52	Color Macro 13
										53-56	Color Macro 14
										57-60	Color Macro 15
										61-64	Color Macro 16
										65-68	Color Macro 17
										69-72	Color Macro 18
										73-76	Color Macro 19
										77-80	Color Macro 20
										81-84	Color Macro 21
										85-88	Color Macro 22
										89-92	Color Macro 23
										93-96	Color Macro 24
										97-100	Color Macro 25
										101-104	Color Macro 26
										105-108	Color Macro 27
										109-112	Color Macro 28
										113-116	Color Macro 29
										117-120	Color Macro 30
121-124	Color Macro 31										
125-128	Color Macro 32										

DMX Channel Values / Functions Version 1 (35 DMX Channels)

Specifications are subject to change without any prior written notice.

*Control of LEDs depends on the Pixel Flip setting.

DMX CHANNEL MODE										VALUE	FUNCTION
1CH:04	2CH:04	6CH	8CH	10CH	12CH	28CH	30CH	32CH	35CH		16 BIT CHANNELS
1			5		5						COLOR MACROS [continued]
										129-132	Color Macro 33
										133-136	Color Macro 34
										137-140	Color Macro 35
										141-144	Color Macro 36
										145-148	Color Macro 37
										149-152	Color Macro 38
										153-156	Color Macro 39
										157-160	Color Macro 40
										161-164	Color Macro 41
										165-168	Color Macro 42
										169-172	Color Macro 43
										173-176	Color Macro 44
										177-180	Color Macro 45
										181-184	Color Macro 46
										185-188	Color Macro 47
										189-192	Color Macro 48
										193-196	Color Macro 49
										197-200	Color Macro 50
										201-204	Color Macro 51
										205-208	Color Macro 52
										209-212	Color Macro 53
										213-216	Color Macro 54
										217-220	Color Macro 55
										221-224	Color Macro 56
										225-228	Color Macro 57
										229-232	Color Macro 58
										233-236	Color Macro 59
										237-240	Color Macro 60
										241-244	Color Macro 61
245-248	Color Macro 62										
249-252	Color Macro 63										
253-255	Color Macro 64										
2			6	5	6			29	29		STROBE
										0-31	NO Function
										32-63	LEDs ON
										64-95	Strobe Effect SLOW to FAST
										96-127	LEDs ON
										128-159	Pulse Effect In Sequence SLOW to FAST
										160-191	LEDs ON
										192-223	Random Strobe Effect SLOW to FAST
224-255	LEDs ON										
3		5	7	6	7		29	30	30		MASTER DIMMER
										0-255	0 to 100%
4		6	8	7	8		30	31	31		FINE DIMMER [16BIT]
										0-256	1 to 100%

DMX Channel Values / Functions Version 1 (35 DMX Channels)

Specifications are subject to change without any prior written notice.

*Control of LEDs depends on the Pixel Flip setting.

DMX CHANNEL MODE										VALUE	FUNCTION
1CH:04	2CH:04	6CH	8CH	10CH	12CH	28CH	30CH	32CH	35CH		16 BIT CHANNELS
											AUTO PROGRAMS
										0	NO FUNCTION
										1-20	PROGRAM MACRO 01
										21-40	PROGRAM MACRO 02
										41-60	PROGRAM MACRO 03
										61-80	PROGRAM MACRO 04
										81-100	PROGRAM MACRO 05
				8	9				32	101-120	PROGRAM MACRO 06
										121-140	PROGRAM MACRO 07
										141-160	PROGRAM MACRO 08
										161-180	PROGRAM MACRO 09
										181-200	PROGRAM MACRO 10
										201-220	PROGRAM MACRO 11
										221-240	PROGRAM MACRO 12
										241-250	PROGRAM MACRO 13
										251-255	PROGRAM MACRO 14
				9	10				33		AUTO PROGRAM SPEED
										0-255	Program Speed SLOW to FAST
				10	11				34		AUTO PROGRAM FADE
										0-255	Program Fade SLOW to FAST
											DIMMING CURVE MODES
										0-20	STANDARD
										21-40	STAGE
										41-60	TV
										61-80	ARCHITECTURAL
										81-100	THEATRE
										101-255	Default to Unit Setting

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040
 323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com

Elation Professional B.V. | Junostraat 2 | 6468 EW Kerkrade, The Netherlands
 +31 45 546 85 66 | +31 45 546 85 96 fax | www.elationlighting.eu | info@elationlighting.eu