

# THERMA TOUR 800 - DMX CHANNEL FUNCTIONS & VALUES

CHANNEL		VALUES	FUNCTION
1-CH	3-CH		
1	1		<b>Fog</b>
		000 - 005	Off
		006 - 255	On
	2		<b>Duration</b>
		000 - 005	Off (0s)
		006 - 255	On, 1s - 250s (steps of 1s)
	3		<b>Interval</b>
		000 - 005	Off (0s)
		006 - 255	On, 10s - 2500s (steps of 10s)