

ELATION KL FRESNEL 6 CW PO - DMX TRAITS

ELATION KL FRESNEL 6 CW PO DMX CHANNEL TRAITS

Supports Software Versions: 1.04

Features subject to change without notice.
Rotation direction (clockwise/counter-clockwise) and control of effects depends on head orientation and pan/tilt settings.

CHANNEL					DMX VALUES	FUNCTION
Dimmer	Dimmer 16bit	3CH	Standard	Extended		
1	1	1	1	1	000 - 255	Dimmer Intensity, 0% to 100%
	2		2	2	000 - 255	Dimmer Intensity Fine
		2	3	3		Strobe
					000 - 031	LED Off
					032 - 063	LED On
					064 - 095	Strobe Effect, slow to fast
					096 - 127	LED On
					128 - 159	Pulse Effect, slow to fast
					160 - 191	LED On
					192 - 223	Random Strobe Effect, slow to fast
					224 - 255	LED On
		3	4	4		Dimmer Modes
					000 - 020	Standard
					021 - 040	Stage
					041 - 060	TV
					061 - 080	Architectural
					081 - 100	Theatre
					101 - 120	Stage 2
						Dimmer Delay Time
					121	0.0s
					122	0.1s
					123	0.2s
					124	0.3s
					125	0.4s
					126	0.5s
					127	0.6s
					128	0.7s
					129	0.8s
		130	0.9s			
		131	1.0s			
		132	1.5s			
		133	2.0s			
		134	3.0s			

CONTINUED ON NEXT PAGE

ELATION KL FRESNEL 6 CW PO - DMX TRAITS

CHANNEL					DMX VALUES	FUNCTION
Dimmer	Dimmer 16bit	3CH	Standard	Extended		
		3	4	4		Dimmer Delay Time (continued)
					135	4.0s
					136	5.0s
					137	6.0s
					138	7.0s
					139	8.0s
					140	9.0s
					141	10.0s
					142 - 255	Default
						Control (hold for 3s)
					000 - 100	Idle
						Refresh Rate
				5	101 - 105	900 Hz
					106 - 110	1000 Hz
					111 - 115	1100 Hz
					116 - 120	1200 Hz (default)
					121 - 125	1300 Hz
					126 - 130	1400 Hz
					131 - 135	1500 Hz
					136 - 140	2500 Hz
					141 - 145	4000 Hz
					146 - 150	5000 Hz
					151 - 155	10,000 Hz
					156 - 160	15,000 Hz
					161 - 165	20,000 Hz
					166 - 170	25,000 Hz
					171 - 200	Idle
						Dimmer Curves
					201 - 210	Linear (default)
				211 - 220	Square	
				221 - 230	Inverse Square	
				231 - 240	S-Curve	
				241 - 255	Idle	