

ELATION® DW FRESNEL™			
DMX Channel Values / Functions (8 DMX Channels)			
Specifications are subject to change without any prior written notice.			
MODE / CHANNEL			FUNCTION
2CH	3CH	8CH	VALUE
1	1	1	
			0-255
2	2	2	
			0-255
		3	
			0
			1-255
		4	
			0
			1-16
			17-33
			34-50
			51-67
			68-84
			85-101
			102-118
			119-135
			136-152
			153-169
			170-186
			187-203
			204-220
			221-237
238-255			
		5	
			0-31
			32-63
			64-95
			96-127
			128-159
			160-191
			192-223
224-255			
	3	6	
			0-255
		7	
			0-255
		8	
			0-41
			42-84
			85-127
			128-170
			171-213
214-255			

ELATION | DW FRESNEL™ | dmx traits

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040

323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com

Elation Professional B.V. | Junostraat 2 | 6468 EW Kerkrade, Netherlands

+31 45 546 85 66 | +31 45 546 85 96 fax | www.elationlighting.eu | info@elationlighting.eu