

ELATION® DESIGN WASH LED ZOOM CW™
DMX Channel Values / Functions [10 DMX Channels]

Specifications are subject to change without any prior written notice.

CHANNEL	VALUE	FUNCTION
1		PAN MOVEMENT [8 Bit]
	0-255	PAN Movement
2		PAN MOVEMENT [16 Bit]
	0-255	Fine Control Of PAN Movement
3		TILT MOVEMENT [8 Bit]
	0-255	TILT Movement
4		TILT MOVEMENT [16 Bit]
	0-255	Fine Control Of TILT Movement
5		SPEED PAN/TILT MOVEMENT
	0-225	Max To Min Speed
	226-235	Blackout By Movement
	236-255	NO Function
6		WHITE LEDs [108 Total]
	0-255	WHITE (0-Black - 255-100%)
7		SHUTTER, STROBE
	0-31	Shutter CLOSED (ALL LEDs OFF)
	32-63	Shutter OPEN (ALL LEDs ON)
	64-95	Strobe Effect SLOW to FAST
	96-127	Shutter OPEN (ALL LEDs ON)
	128-159	Pulse Effect In Sequences
	160-191	Shutter OPEN (ALL LEDs ON)
	192-223	Random Strobe Effect SLOW to FAST
224-255	Shutter OPEN (ALL LEDs ON)	
8		DIMMER INTENSITY
	0-255	Intensity 0 to 100%
9		ZOOM
	0-255	Zoom
10		RESET INTERNAL PROGRAMS
	0-79	Normal
	80-84	ALL Motor Reset
	85-87	SCAN Motor Reset
	88-99	NO Function
	100-119	Internal Program 1 (Scene 1 - 8)
	120-139	Internal Program 2 (Scene 9 - 16)
	140-159	Internal Program 3 (Scene 17 - 24)
	160-179	Internal Program 4 (Scene 25 - 32)
	180-199	Internal Program 5 (Scene 33 - 40)
	200-219	Internal Program 6 (Scene 41 - 48)
	220-239	Internal Program 7 (Scene 49 - 56)
240-255	Sound Control (Scene of Program 1)	

ELATION | **DESIGN WASH LED ZOOM CW™** | dmx traits

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040

323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com

Elation Professional B.V. | Junostraat 2 | 6468 EW Kerkrade, Netherlands

+31 45 546 85 66 | +31 45 546 85 96 fax | www.elationlighting.eu | info@elationlighting.eu