

**ELATION® LEVEL Q7 IP™**

**DMX Channel Values / Functions - VERSION 1 (9 DMX Channels)**

Specifications are subject to change without any prior written notice.

MODE / CHANNEL				VALUE	FUNCTION
4	5	7	9		
1	1	1	1		<b>RED - All LEDs</b>
				0-255	Red ( 0-Black , 255-100% Red )
2	2	2	2		<b>GREEN - All LEDs</b>
				0-255	Green ( 0-Black , 255-100% Green )
3	3	3	3		<b>BLUE - All LEDs</b>
				0-255	Blue ( 0-Black , 255-100% Blue )
4	4	4	4		<b>WHITE - All LEDs</b>
				0-255	White ( 0-Black , 255-100% White )
		5	5		<b>COLOR CORRECTION</b>
				0	NO Function
				1-255	1=2,700k ~ 255=7,200k
		6	6		<b>COLOR MACROS</b>
				0	NO Function
				1-7	Color Macro 1
				8-15	Color Macro 2
				16-23	Color Macro 3
				24-31	Color Macro 4
				32-39	Color Macro 5
				40-47	Color Macro 6
				48-55	Color Macro 7
				56-63	Color Macro 8
				64-71	Color Macro 9
				72-79	Color Macro 10
				80-87	Color Macro 11
				88-95	Color Macro 12
				96-103	Color Macro 13
				104-111	Color Macro 14
				112-119	Color Macro 15
				120-127	Color Macro 16
				128-135	Color Macro 17
				136-143	Color Macro 18
				144-151	Color Macro 19
				152-159	Color Macro 20
				160-167	Color Macro 21
				168-175	Color Macro 22
				176-183	Color Macro 23
				184-191	Color Macro 24
				192-199	Color Macro 25
				200-207	Color Macro 26
				208-215	Color Macro 27
				216-223	Color Macro 28
				224-231	Color Macro 29
				233-239	Color Macro 30
		240-247	Color Macro 31		
		248-255	Color Macro 32		

**ELATION** | LEVEL Q7 IP™ | dmx traits

**ELATION® LEVEL Q7 IP™****DMX Channel Values / Functions - VERSION 1 (9 DMX Channels)**

Specifications are subject to change without any prior written notice.

MODE / CHANNEL				VALUE	FUNCTION
4	5	7	9		
			7		<b>CHASE MACROS</b>
				0	NO Function
				1-30	Chase Macro 1
				31-60	Chase Macro 2
				61-90	Chase Macro 3
				91-120	Chase Macro 4
				121-150	Chase Macro 5
				151-180	Chase Macro 6
				181-210	Chase Macro 7
				211-255	Chase Macro 8
			8		<b>SHUTTER, STROBE</b>
				0-31	All LEDs OFF
				32-63	All LEDs ON
				64-95	Strobe Effect SLOW to FAST
				96-127	All LEDs ON
				128-159	Pulse Effect In Sequences SLOW to FAST
				160-191	All LEDs ON
				192-223	Random Strobe Effect SLOW to FAST
			224-255	All LEDs ON	
	5	7	9		<b>DIMMER INTENSITY</b>
				0-255	Intensity 0 to 100%

**Elation Professional USA** | 6122 S. Eastern Ave. | Los Angeles, CA. 90040

323-582-3322 | 323-832-9142 fax | [www.elationlighting.com](http://www.elationlighting.com) | [info@elationlighting.com](mailto:info@elationlighting.com)

**Elation Professional B.V.** | Junostraat 2 | 6468 EW Kerkrade, Netherlands

+31 45 546 85 66 | +31 45 546 85 96 fax | [www.elationlighting.eu](http://www.elationlighting.eu) | [info@elationlighting.eu](mailto:info@elationlighting.eu)