

ELATION® OPTI QUAD PAR™
DMX Channel Values / Functions VERSION 1 (8 DMX Channels)

Specifications are subject to change without any prior written notice.

MODE / CHANNEL						VALUE	FUNCTION
1 CH	2 CH	4 CH	5 CH	7 CH	8 CH		
		1	1	1	1		RED* *RED Control Disabled when fixture is in 7 CH or 8 CH Mode and CH 5 Color Macros are being used.
						0-255	RED (0-100%)
		2	2	2	2		GREEN* *GREEN Control Disabled when fixture is in 7 CH or 8 CH Mode and CH 5 Color Macros are being used.
						0-255	GREEN (0-100%)
		3	3	3	3		BLUE* *BLUE Control Disabled when fixture is in 7 CH or 8 CH Mode and CH 5 Color Macros are being used.
						0-256	BLUE (0-100%)
		4	4	4	4		WHITE* *WHITE Control Disabled when fixture is in 7 CH or 8 CH Mode and CH 5 Color Macros are being used.
						0-255	WHITE (0-100%)
							COLOR MACROS
						0	OFF
						1-7	COLOR MACRO 1
						8-15	COLOR MACRO 2
						16-23	COLOR MACRO 3
						24-31	COLOR MACRO 4
						32-39	COLOR MACRO 5
						40-47	COLOR MACRO 6
						48-55	COLOR MACRO 7
						56-63	COLOR MACRO 8
						64-71	COLOR MACRO 9
						72-79	COLOR MACRO 10
						80-87	COLOR MACRO 11
						88-95	COLOR MACRO 12
						96-103	COLOR MACRO 13
						104-111	COLOR MACRO 14
						112-119	COLOR MACRO 15
						120-127	COLOR MACRO 16
						128-135	COLOR MACRO 17
						136-143	COLOR MACRO 18
						144-151	COLOR MACRO 19
						152-159	COLOR MACRO 20
						160-167	COLOR MACRO 21
						168-175	COLOR MACRO 22
						176-183	COLOR MACRO 23
						184-191	COLOR MACRO 24
						192-199	COLOR MACRO 25
						200-207	COLOR MACRO 26
						208-215	COLOR MACRO 27
						216-223	COLOR MACRO 28
						224-231	COLOR MACRO 29
						232-239	COLOR MACRO 30
						240-247	COLOR MACRO 31
						248-255	COLOR MACRO 32
							STROBE / SPEED*
							*SPEED Control ONLY available when fixture is in 8 CH Mode and CH 7 DMX Value is [128-223]
				6		0-255	STROBE Effect SLOW to FAST
					6	0-15	NO STROBE / OFF
						16-255	STROBE Effect SLOW to FAST
						0-255	*SPEED Control SLOW to FAST

ELATION | **OPTI QUAD PAR™** | **dmx traits**

ELATION© OPTI QUAD PAR™							
DMX Channel Values / Functions VERSION 1 (8 DMX Channels)							
Specifications are subject to change without any prior written notice.							
MODE / CHANNEL						VALUE	FUNCTION
1 CH	2 CH	4 CH	5 CH	7 CH	8 CH		
					7		MODE*
							*CH 1, 2, 3, & 4 are used when fixture is in 8 CH Mode and CH 7 DMX Value is (1-128)
						0-127	Color Adjustment
						128-159	Automatic COLOR Mixing
						160-191	3 COLOR Change
						192-223	7 COLOR Change
						224-255	32 COLOR MACRO SOUND Active
	2		5	7	8		DIMMER INTENSITY
						0-255	Intensity 0 to 100%

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040
 323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com

Elation Professional B.V. | Junostraat 2 | 6468 EW Kerkrade, Netherlands
 +31 45 546 85 66 | +31 45 546 85 96 fax | www.elationlighting.eu | info@elationlighting.eu