

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value	
Main Fixture	1		1	1		1	1	1		0-255	Master Dimmer Intensity 0 → 100%		0	
		1	2	2	1	2	2	2		0-255	Strobe Dimmer Intensity 0 → 100%		0	
	2	2	3	3	2	3	3	3		0-255	CW Strobe Duration Min → Max		0	
	3	3	4	4	3	4	4	4		0-255	CW Strobe Rate Fast → Slow		0	
												CW Strobe Mode		
											0-31	Single Strobe/Standard Mode		
											32-63	Ramp Up		
											64-95	Ramp Down		
		4	5	5	4	5	5	5			96-127	Ramp Up → Ramp Down	X	25
											128-159	Random		
											160-191	Double Flash		
											192-223	Triple Flash		
											224-255	No Effect		
		5	6	6	5	6	6	6		0-255	RGB Dimmer Intensity 0 → 100%		0	
		6	7	7	6	7	7	7		0-255	RGB Strobe Duration Min → Max		0	
		7	8	8	7	8	8	8		0-255	RGB Strobe Rate Fast → Slow		0	
												RGB Strobe Mode		
											0-31	Single Strobe/Standard Mode		
											32-63	Ramp Up		
											64-95	Ramp Down		
		8	9	9	8	9	9	9			96-127	Ramp Up → Ramp Down	X	25
											128-159	Random		
											160-191	Double Flash		
											192-223	Triple Flash		
										224-225	Sync Dim and Strobe w/CW Strobe			
										226-255	No Effect			
	9	10	10	9	10	10	10		0-255	All Red Red Saturation 0 → 100%		0		
	10	11	11	10	11	11	11		0-255	All Green Green Saturation 0 → 100%		0		
	11	12	12	11	12	12	12		0-255	All Blue Blue Saturation 0 → 100%		0		

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
Main Fixture			13				13	13		0-255	CW Strobe Effect Selection FX Selection 1 → 255	X	0
			14				14	14			CW Strobe Effect Speed 0-126 Slow → Fast 127-128 Stop 129-255 Rev Fast → Slow		0
			15				15	15			CW Strobe Effect Size 0-50 Idle 51-60 1 Zone 61-70 2 Zone 71-80 4 Zone 81-90 8 Zone 91-100 10 Zone 101-110 20 Zone 111-120 40 Zone 121-255 Idle	X	0
			16				16	16			CW Strobe Effect Offset 0 Idle 1 Fixture Offset 10 Degrees 2 Fixture Offset 20 Degrees 3-34 Fixture Offset... 35 Fixture Offset 350 Degrees 36 Synchronized 37-49 Random Fixture Offset 50-59 Random Pixel Order 60-69 Random Steps 70-79 Idle Effect Fade 80-89 Sinewave- Cross 90-99 Sinewave- Full 100-109 Sawtooth- Cross 110-119 Sawtooth- Full 120-129 Ramp Up 130-139 Ramp Down 140-149 Steps 150-255 Idle	X	0
			17				17	17		0-255	RGB Effect Selection FX Selection 1 → 255	X	0
			18				18	18			RGB Effect Speed 0-126 Slow → Fast 127-128 Stop 129-255 Rev Fast → Slow		0
			19				19	19			RGB Effect Size 0-50 Idle 51-60 1 Zone 61-70 2 Zone 71-80 3 Zone 81-90 6 Zone 91-100 10 Zone 101-110 15 Zone 111-120 20 Zone 121-130 30 Zone 131-140 60 Zone 141-255 Idle	X	0

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value	
Main Fixture			20				20	20			RGB Effect Offset	X	0	
										0	Idle			
										1	Fixture Offset 10 Degrees			
										2	Fixture Offset 20 Degrees			
										3-34	Fixture Offset...			
										35	Fixture Offset 350 Degrees			
										36	Synchronized			
										37-49	Random Fixture Offset			
										50-59	Random Pixel Order			
										60-69	Random Steps			
										70-79	Idle			
											Effect Fade			
										80-89	Sinewave- Cross			
										90-99	Sinewave- Full			
										100-109	Sawtooth- Cross			
										110-119	Sawtooth- Full			
										120-129	Ramp Up			
										130-139	Ramp Down			
	140-149	Steps												
	150-255	Idle												
				21	13		13	21	21			Dim Modes	X	0
											0-20	Standard		
											21-40	Stage		
											41-60	TV		
											61-80	Architectural		
											81-100	Theatre		
											101-120	Stage 2		
												Dimmer Delay Time		
											121	0s		
											122	0.1s		
											123	0.2s		
											124	0.3s		
											125	0.4s		
											126	0.5s		
127											0.6s			
128											0.7s			
129											0.8s			
130											0.9s			
131											1.0s			
132											1.5s			
133											2.0s			
134											3.0s			
135											4.0s			
136											5.0s			
137											6.0s			
138											7.0s			
139											8.0s			
140	9.0s													
141	10s													
142-255	Idle													

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
Main Fixture											Control		
										0-99	Idle		
											Refresh Rate (Hz)		
										100	900		
										101	910		
										102	920		
										103	930		
										104	940		
										105	950		
										106	960		
										107	970		
										108	980		
										109	990		
										110	1000		
										111	1010		
										112	1020		
										113	1030		
										114	1040		
										115	1050		
										116	1060		
										117	1070		
										118	1080		
										119	1090		
				22	14	12	14	22	22	120	1100	X	0
										121	1110		
										122	1120		
										123	1130		
										124	1140		
										125	1150		
										126	1160		
									127	1170			
									128	1180			
									129	1190			
									130	1200			
									131	1210			
									132	1220			
									133	1230			
									134	1240			
									135	1250			
									136	1260			
									137	1270			
									138	1280			
									139	1290			
									140	1300			
									141	1310			
									142	1320			
									143	1330			

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
Main Fixture										144	1340		
										145	1350		
										146	1360		
										147	1370		
										148	1380		
										149	1390		
										150	1400		
										151	1410		
										152	1420		
										153	1430		
										154	1440		
										155	1450		
										156	1460		
										157	1470		
										158	1480		
										159	1490		
										160	1500		
										161	2500		
										162	4000		
										163	5000		
										164	6000		
										165	10000		
				22	14	12	14	22	22	166	15000		
										167	20000	X	0
										168	25000		
										169-170	Idle		
											Zone Flip		
										171-172	Default Zone Arrangement		
										173-174	Flip Zones Horizontally		
										175-176	Flip Zones Vertically		
										177-178	Flip Zones Horizontally and Vertically		
										179-183	Idle		
											Zone Linking		
										184-185	RGB Strobeline to Default		
										186-187	RGB StrobeLine Link to Top Center CW Strobe		
										188-189	RGB StrobeLine Link to Top RGB		
										190-191	RGB StrobeLine to Bottom RGB		
										192-193	RGB StrobeLine Inactive		
										194-200	Idle		
											Dimmer Curves		
									201-210	Dimmer Curve: Linear (Default)			
									211-220	Dimmer Curve: Square			
									221-230	Dimmer Curve: Inverse Square			
									231-240	Dimmer Curve: S-Curve			
									241-255	Idle			

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
Pixel 1				15	13	15	23	23	1	0-255	Red 1 Red Saturation 0 → 100%		0
				16	14	16	24	24	2	0-255	Green 1 Green Saturation 0 → 100%		0
				17	15	17	25	25	3	0-255	Blue 1 Blue Saturation 0 → 100%		0
Pixel 2				18	16	18	26	26	4	0-255	Red 2 Red Saturation 0 → 100%		0
				19	17	19	27	27	5	0-255	Green 2 Green Saturation 0 → 100%		0
				20	18	20	28	28	6	0-255	Blue 2 Blue Saturation 0 → 100%		0
Pixel 3				21	19	21	29	29	7	0-255	Red 3 Red Saturation 0 → 100%		0
				22	20	22	30	30	8	0-255	Green 3 Green Saturation 0 → 100%		0
				23	21	23	31	31	9	0-255	Blue 3 Blue Saturation 0 → 100%		0
Pixel 4				24	22	24	32	32	10	0-255	Red 4 Red Saturation 0 → 100%		0
				25	23	25	33	33	11	0-255	Green 4 Green Saturation 0 → 100%		0
				26	24	26	34	34	12	0-255	Blue 4 Blue Saturation 0 → 100%		0
Pixel 5				27	25	27	35	35	13	0-255	Red 5 Red Saturation 0 → 100%		0
				28	26	28	36	36	14	0-255	Green 5 Green Saturation 0 → 100%		0
				29	27	29	37	37	15	0-255	Blue 5 Blue Saturation 0 → 100%		0
Pixel 6				30	28	30	38	38	16	0-255	Red 6 Red Saturation 0 → 100%		0
				31	29	31	39	39	17	0-255	Green 6 Green Saturation 0 → 100%		0
				32	30	32	40	40	18	0-255	Blue 6 Blue Saturation 0 → 100%		0
Pixel 7				33	31	33	41	41	19	0-255	Red 7 Red Saturation 0 → 100%		0
				34	32	34	42	42	20	0-255	Green 7 Green Saturation 0 → 100%		0
				35	33	35	43	43	21	0-255	Blue 7 Blue Saturation 0 → 100%		0
Pixel 8				36	34	36	44	44	22	0-255	Red 8 Red Saturation 0 → 100%		0
				37	35	37	45	45	23	0-255	Green 8 Green Saturation 0 → 100%		0
				38	36	38	46	46	24	0-255	Blue 8 Blue Saturation 0 → 100%		0
Pixel 9					37	39	47	47	25	0-255	Red 9 Red Saturation 0 → 100%		0
					38	40	48	48	26	0-255	Green 9 Green Saturation 0 → 100%		0
					39	41	49	49	27	0-255	Blue 9 Blue Saturation 0 → 100%		0
Pixel 10					40	42	50	50	28	0-255	Red 10 Red Saturation 0 → 100%		0
					41	43	51	51	29	0-255	Green 10 Green Saturation 0 → 100%		0
					42	44	52	52	30	0-255	Blue 10 Blue Saturation 0 → 100%		0

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
Pixel 11					43	45	53	3	31	0-255	Red 11 Red Saturation 0 → 100%		0
					44	46	54	54	32	0-255	Green 11 Green Saturation 0 → 100%		0
					45	47	55	55	33	0-255	Blue 11 Green Saturation 0 → 100%		0
Pixel 12					46	48	56	56	34	0-255	Red 12 Red Saturation 0 → 100%		0
					47	49	57	57	35	0-255	Green 12 Green Saturation 0 → 100%		0
					48	50	58	8	36	0-255	Blue 12 Blue Saturation 0 → 100%		0
Pixel 13					49	51	59	59	37	0-255	Red 13 Red Saturation 0 → 100%		0
					50	52	60	60	38	0-255	Green 13 Green Saturation 0 → 100%		0
					51	53	61	61	39	0-255	Blue 13 Blue Saturation 0 → 100%		0
Pixel 14					52	54	62	62	40	0-255	Red 14 Red Saturation 0 → 100%		0
					53	55	63	63	41	0-255	Green 14 Green Saturation 0 → 100%		0
					54	56	64	64	42	0-255	Blue 14 Blue Saturation 0 → 100%		0
Pixel 15					55	57	65	65	43	0-255	Red 15 Red Saturation 0 → 100%		0
					56	58	66	66	44	0-255	Green 15 Green Saturation 0 → 100%		0
					57	59	67	67	45	0-255	Blue 15 Blue Saturation 0 → 100%		0
Pixel 16					58	60	68	68	46	0-255	Red 16 Red Saturation 0 → 100%		0
					59	61	69	69	47	0-255	Green 16 Green Saturation 0 → 100%		0
					60	62	70	70	48	0-255	Blue 16 Blue Saturation 0 → 100%		0
Pixel 17					61	63	71	71	49	0-255	Red 17 Red Saturation 0 → 100%		0
					62	64	72	72	50	0-255	Green 17 Green Saturation 0 → 100%		0
					63	65	73	73	51	0-255	Blue 17 Blue Saturation 0 → 100%		0
Pixel 18					64	66	74	74	52	0-255	Red 18 Red Saturation 0 → 100%		0
					65	67	75	75	53	0-255	Green 18 Green Saturation 0 → 100%		0
					66	68	76	76	54	0-255	Blue 18 Blue Saturation 0 → 100%		0
Pixel 19					67	69	77	77	55	0-255	Red 19 Red Saturation 0 → 100%		0
					68	70	78	78	56	0-255	Green 19 Green Saturation 0 → 100%		0
					69	71	79	79	57	0-255	Blue 19 Blue Saturation 0 → 100%		0
Pixel 20					70	72	80	80	58	0-255	Red 20 Red Saturation 0 → 100%		0
					71	73	81	81	59	0-255	Green 20 Green Saturation 0 → 100%		0
					72	74	82	82	60	0-255	Blue 20 Blue Saturation 0 → 100%		0

ELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
Pixel 21						75		83	61	0-255	Red 25651 Red Saturation 0 → 100%		0
						76		84	62	0-255	Green 21 Green Saturation 0 → 100%		0
						77		85	63	0-255	Blue 21 Green Saturation 0 → 100%		0
Pixel 22						78		86	64	0-255	Red 22 Red Saturation 0 → 100%		0
						79		87	65	0-255	Green 22 Green Saturation 0 → 100%		0
						80		88	66	0-255	Blue 22 Blue Saturation 0 → 100%		0
Pixel 23						81		89	67	0-255	Red 23 Red Saturation 0 → 100%		0
						82		90	68	0-255	Green 23 Green Saturation 0 → 100%		0
						83		91	69	0-255	Blue 23 Blue Saturation 0 → 100%		0
Pixel 24						84		92	70	0-255	Red 24 Red Saturation 0 → 100%		0
						85		93	71	0-255	Green 24 Green Saturation 0 → 100%		0
						86		94	72	0-255	Blue 24 Blue Saturation 0 → 100%		0
Pixel 25						87		95	73	0-255	Red 25 Red Saturation 0 → 100%		0
						88		96	74	0-255	Green 25 Green Saturation 0 → 100%		0
						89		97	75	0-255	Blue 25 Blue Saturation 0 → 100%		0
Pixel 26						90		98	76	0-255	Red 26 Red Saturation 0 → 100%		
						91		99	77	0-255	Green 26 Green Saturation 0 → 100%		0
						92		100	78	0-255	Blue 26 Blue Saturation 0 → 100%		0
Pixel 27						93		101	79	0-255	Red 27 Red Saturation 0 → 100%		0
						94		102	80	0-255	Green 27 Green Saturation 0 → 100%		0
						95		103	81	0-255	Blue 27 Blue Saturation 0 → 100%		0
Pixel 28						96		104	82	0-255	Red 28 Red Saturation 0 → 100%		0
						97		105	83	0-255	Green 28 Green Saturation 0 → 100%		0
						98		106	84	0-255	Blue 28 Blue Saturation 0 → 100%		0
Pixel 29						99		107	85	0-255	Red 29 Red Saturation 0 → 100%		0
						100		108	86	0-255	Green 229 Green Saturation 0 → 100%		0
						101		109	87	0-255	Blue 29 Blue Saturation 0 → 100%		0
Pixel 30						102		110	88	0-255	Red 30 Red Saturation 0 → 100%		0
						103		111	89	0-255	Green 30 Green Saturation 0 → 100%		0
						104		112	90	0-255	Blue 30 Blue Saturation 0 → 100%		0

ELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
Pixel 31						105		113	91	0-255	Red 361 Red Saturation 0 → 100%		0
						106		114	92	0-255	Green 31 Green Saturation 0 → 100%		0
						107		115	93	0-255	Blue 31 Green Saturation 0 → 100%		0
Pixel 32						108		116	94	0-255	Red 32 Red Saturation 0 → 100%		0
						109		117	95	0-255	Green 32 Green Saturation 0 → 100%		0
						110		118	96	0-255	Blue 32 Blue Saturation 0 → 100%		0
Pixel 33						111		119	97	0-255	Red 33 Red Saturation 0 → 100%		0
						112		120	98	0-255	Green 33 Green Saturation 0 → 100%		0
						113		121	99	0-255	Blue 33 Blue Saturation 0 → 100%		0
Pixel 34						114		122	100	0-255	Red 34 Red Saturation 0 → 100%		0
						115		123	101	0-255	Green 34 Green Saturation 0 → 100%		0
						116		124	102	0-255	Blue 34 Blue Saturation 0 → 100%		0
Pixel 35						117		125	103	0-255	Red 35 Red Saturation 0 → 100%		0
						118		126	104	0-255	Green 35 Green Saturation 0 → 100%		0
						119		127	105	0-255	Blue 35 Blue Saturation 0 → 100%		0
Pixel 36						120		128	106	0-255	Red 36 Red Saturation 0 → 100%		
						121		129	107	0-255	Green 36 Green Saturation 0 → 100%		0
						122		130	108	0-255	Blue 36 Blue Saturation 0 → 100%		0
Pixel 37						123		131	109	0-255	Red 37 Red Saturation 0 → 100%		0
						124		132	110	0-255	Green 37 Green Saturation 0 → 100%		0
						125		133	111	0-255	Blue 37 Blue Saturation 0 → 100%		0
Pixel 38						126		134	112	0-255	Red 38 Red Saturation 0 → 100%		0
						127		135	113	0-255	Green 38 Green Saturation 0 → 100%		0
						128		136	114	0-255	Blue 38 Blue Saturation 0 → 100%		0
Pixel 39						129		137	115	0-255	Red 39 Red Saturation 0 → 100%		0
						130		138	116	0-255	Green 39 Green Saturation 0 → 100%		0
						131		139	117	0-255	Blue 39 Blue Saturation 0 → 100%		0
Pixel 40						132		140	118	0-255	Red 40 Red Saturation 0 → 100%		0
						133		141	119	0-255	Green 40 Green Saturation 0 → 100%		0
						134		142	120	0-255	Blue 40 Blue Saturation 0 → 100%		0

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
CW Strobe 1				39	73	135	83	143	121	0-255	CW Strobe 1		0
											Intensity 0 → 100%		
CW Strobe 2				40	74	136	84	144	122	0-255	CW Strobe 2		0
											Intensity 0 → 100%		
CW Strobe 3					75	137	85	145	123	0-255	CW Strobe 3		0
											Intensity 0 → 100%		
CW Strobe 4					76	138	86	146	124	0-255	CW Strobe 4		0
											Intensity 0 → 100%		
CW Strobe 5					77	139	87	147	125	0-255	CW Strobe 5		0
											Intensity 0 → 100%		
CW Strobe 6					78	140	88	148	126	0-255	CW Strobe 6		0
											Intensity 0 → 100%		
CW Strobe 7					79	141	89	149	127	0-255	CW Strobe 7		0
											Intensity 0 → 100%		
CW Strobe 8					80	142	90	150	128	0-255	CW Strobe 8		0
											Intensity 0 → 100%		
CW Strobe 9					81	143	91	151	129	0-255	CW Strobe 9		0
											Intensity 0 → 100%		
CW Strobe 10					82	144	92	152	130	0-255	CW Strobe 10		0
											Intensity 0 → 100%		
CW Strobe 11					83	145	93	153	131	0-255	CW Strobe 11		0
											Intensity 0 → 100%		
CW Strobe 12					84	146	94	154	132	0-255	CW Strobe 12		0
											Intensity 0 → 100%		
CW Strobe 13					85	147	95	155	133	0-255	CW Strobe 13		0
											Intensity 0 → 100%		
CW Strobe 14					86	148	96	156	134	0-255	CW Strobe 14		0
											Intensity 0 → 100%		
CW Strobe 15					87	149	97	157	135	0-255	CW Strobe 15		0
											Intensity 0 → 100%		
CW Strobe 16					88	150	98	158	136	0-255	CW Strobe 16		0
											Intensity 0 → 100%		
CW Strobe 17					89	151	99	159	137	0-255	CW Strobe 17		0
											Intensity 0 → 100%		
CW Strobe 18					90	152	100	160	138	0-255	CW Strobe 18		0
											Intensity 0 → 100%		
CW Strobe 19					91	153	101	161	139	0-255	CW Strobe 19		0
											Intensity 0 → 100%		
CW Strobe 20					92	154	102	162	140	0-255	CW Strobe 20		0
											Intensity 0 → 100%		

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
CW Strobe 21						155		163	141	0-255	CW Strobe 21		0
											Intensity 0 → 100%		
CW Strobe 22						156		164	142	0-255	CW Strobe 22		0
											Intensity 0 → 100%		
CW Strobe 23						157		165	143	0-255	CW Strobe 23		0
											Intensity 0 → 100%		
CW Strobe 24						158		166	144	0-255	CW Strobe 24		0
											Intensity 0 → 100%		
CW Strobe 25						159		167	145	0-255	CW Strobe 25		0
											Intensity 0 → 100%		
CW Strobe 26						160		168	146	0-255	CW Strobe 26		0
											Intensity 0 → 100%		
CW Strobe 27						161		169	147	0-255	CW Strobe 27		0
											Intensity 0 → 100%		
CW Strobe 28						162		170	148	0-255	CW Strobe 28		0
											Intensity 0 → 100%		
CW Strobe 29						163		171	149	0-255	CW Strobe 29		0
											Intensity 0 → 100%		
CW Strobe 30						164		172	150	0-255	CW Strobe 30		0
											Intensity 0 → 100%		
CW Strobe 31						165		173	151	0-255	CW Strobe 31		0
											Intensity 0 → 100%		
CW Strobe 32						166		174	152	0-255	CW Strobe 32		0
											Intensity 0 → 100%		
CW Strobe 33						167		175	153	0-255	CW Strobe 33		0
											Intensity 0 → 100%		
CW Strobe 34						168		176	154	0-255	CW Strobe 34		0
											Intensity 0 → 100%		
CW Strobe 35						169		177	155	0-255	CW Strobe 35		0
											Intensity 0 → 100%		
CW Strobe 36						170		178	156	0-255	CW Strobe 36		0
											Intensity 0 → 100%		
CW Strobe 37						171		179	157	0-255	CW Strobe 37		0
											Intensity 0 → 100%		
CW Strobe 38						172		180	158	0-255	CW Strobe 38		0
											Intensity 0 → 100%		
CW Strobe 39						173		181	159	0-255	CW Strobe 39		0
											Intensity 0 → 100%		
CW Strobe 40						174		182	160	0-255	CW Strobe 40		0
											Intensity 0 → 100%		

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
RGB StrobeLine 1				41		175	103	183	161	0-255	StrobeLine Red 1 Red Saturation 0 → 100%		0
				42		176	104	187	162	0-255	StrobeLine Green 1 Green Saturation 0 → 100%		0
				43		177	105	185	163	0-255	StrobeLine Blue 1 Blue Saturation 0 → 100%		0
RGB StrobeLine 2				44		178	106	186	164	0-255	StrobeLine Red 2 Red Saturation 0 → 100%		0
				45		179	107	187	165	0-255	StrobeLine Green 2 Green Saturation 0 → 100%		0
				46		180	108	188	166	0-255	StrobeLine Blue 2 Blue Saturation 0 → 100%		0
RGB StrobeLine 3				47		181	109	189	167	0-255	StrobeLine Red 3 Red Saturation 0 → 100%		0
				48		182	110	190	168	0-255	StrobeLine Green 3 Green Saturation 0 → 100%		0
				49		183	111	191	169	0-255	StrobeLine Blue 3 Blue Saturation 0 → 100%		0
RGB StrobeLine 4				50		184	112	192	170	0-255	StrobeLine Red 4 Red Saturation 0 → 100%		0
				51		185	113	193	171	0-255	StrobeLine Green 4 Green Saturation 0 → 100%		0
				52		186	114	194	172	0-255	StrobeLine Blue 4 Blue Saturation 0 → 100%		0
RGB StrobeLine 5						187	115	195	173	0-255	StrobeLine Red 5 Red Saturation 0 → 100%		0
						188	116	196	174	0-255	StrobeLine Green 5 Green Saturation 0 → 100%		0
						189	117	197	175	0-255	StrobeLine Blue 5 Blue Saturation 0 → 100%		0
RGB StrobeLine 6						190	118	198	176	0-255	StrobeLine Red 6 Red Saturation 0 → 100%		0
						191	119	199	177	0-255	StrobeLine Green 6 Green Saturation 0 → 100%		0
						192	120	200	178	0-255	StrobeLine Blue 6 Blue Saturation 0 → 100%		0
RGB StrobeLine 7						193	121	201	179	0-255	StrobeLine Red 7 Red Saturation 0 → 100%		0
						194	122	202	180	0-255	StrobeLine Green 7 Green Saturation 0 → 100%		0
						195	123	203	181	0-255	StrobeLine Blue 7 Blue Saturation 0 → 100%		0
RGB StrobeLine 8						196	124	204	182	0-255	StrobeLine Red 8 Red Saturation 0 → 100%		0
						197	125	205	183	0-255	StrobeLine Green 8 Green Saturation 0 → 100%		0
						198	126	206	184	0-255	StrobeLine Blue 8 Blue Saturation 0 → 100%		0
RGB StrobeLine 9						199	127	207	185	0-255	StrobeLine Red 9 Red Saturation 0 → 100%		0
						200	128	208	186	0-255	StrobeLine Green 9 Green Saturation 0 → 100%		0
						201	129	209	187	0-255	StrobeLine Blue 9 Blue Saturation 0 → 100%		0
RGB StrobeLine 10						202	130	210	188	0-255	StrobeLine Red 10 Red Saturation 0 → 100%		0
						203	131	211	189	0-255	StrobeLine Green 10 Green Saturation 0 → 100%		0
						204	132	212	190	0-255	StrobeLine Blue 10 Blue Saturation 0 → 100%		0

RELATION PULSE BAR L - DMX TRAITS

Fixture Part Name	Xenon Strobe 3CH	Simple Strobe 11CH	Strobe FX 22CH	Large Pixels 52CH	Simple Pixel 92CH	Pixel Focus 234CH	Basic Full 132CH	Full Ctrl 242CH	Raw Mode 220CH	DMX Values	Function	Snap	Default Value
RGB StrobeLine 11						205		213	191	0-255	StrobeLine Red 11 Red Saturation 0 → 100%		0
						206		214	192	0-255	StrobeLine Green 11 Green Saturation 0 → 100%		0
						207		215	193	0-255	StrobeLine Blue 11 Blue Saturation 0 → 100%		0
RGB StrobeLine 12						208		216	194	0-255	StrobeLine Red 12 Red Saturation 0 → 100%		0
						209		217	195	0-255	StrobeLine Green 12 Green Saturation 0 → 100%		0
						210		218	196	0-255	StrobeLine Blue 12 Blue Saturation 0 → 100%		0
RGB StrobeLine 13						211		219	197	0-255	StrobeLine Red 13 Red Saturation 0 → 100%		0
						212		220	198	0-255	StrobeLine Green 13 Green Saturation 0 → 100%		0
						213		221	199	0-255	StrobeLine Blue 13 Blue Saturation 0 → 100%		0
RGB StrobeLine 14						214		222	200	0-255	StrobeLine Red 14 Red Saturation 0 → 100%		0
						215		223	201	0-255	StrobeLine Green 14 Green Saturation 0 → 100%		0
						216		224	202	0-255	StrobeLine Blue 14 Blue Saturation 0 → 100%		0
RGB StrobeLine 15						217		225	203	0-255	StrobeLine Red 15 Red Saturation 0 → 100%		0
						218		226	204	0-255	StrobeLine Green 15 Green Saturation 0 → 100%		0
						219		227	205	0-255	StrobeLine Blue 15 Blue Saturation 0 → 100%		0
RGB StrobeLine 16						220		228	206	0-255	StrobeLine Red 16 Red Saturation 0 → 100%		0
						221		229	207	0-255	StrobeLine Green 16 Green Saturation 0 → 100%		0
						222		230	208	0-255	StrobeLine Blue 16 Blue Saturation 0 → 100%		0
RGB StrobeLine 17						223		231	209	0-255	StrobeLine Red 17 Red Saturation 0 → 100%		0
						224		232	210	0-255	StrobeLine Green 17 Green Saturation 0 → 100%		0
						225		233	211	0-255	StrobeLine Blue 17 Blue Saturation 0 → 100%		0
RGB StrobeLine 18						226		234	212	0-255	StrobeLine Red 18 Red Saturation 0 → 100%		0
						227		235	213	0-255	StrobeLine Green 18 Green Saturation 0 → 100%		0
						228		236	214	0-255	StrobeLine Blue 18 Blue Saturation 0 → 100%		0
RGB StrobeLine 19						229		237	215	0-255	StrobeLine Red 19 Red Saturation 0 → 100%		0
						230		238	216	0-255	StrobeLine Green 19 Green Saturation 0 → 100%		0
						231		239	217	0-255	StrobeLine Blue 19 Blue Saturation 0 → 100%		0
RGB StrobeLine 20						232		240	218	0-255	StrobeLine Red 20 Red Saturation 0 → 100%		0
						233		241	219	0-255	StrobeLine Green 20 Green Saturation 0 → 100%		0
						234		242	220	0-255	StrobeLine Blue 20 Blue Satruation 0 → 100%		0